

FRAME-TYPE FAMILIES OF TRANSLATES

SHAHAF NITZAN-HAHAMOV AND ALEXANDER OLEVSKII

School of Mathematical Sciences, Tel Aviv University, Ramat-Aviv, Israel
69978

e-mail addresses: olevskii@math.tau.ac.il
nitzansi@post.tau.ac.il

ABSTRACT. We construct a uniformly discrete, and even sparse, sequence of real numbers $\Lambda = \{\lambda_n\}$ and a function $g \in L^2(\mathbb{R})$, such that for every $q > 2$, every function $f \in L^2(\mathbb{R})$ can be approximated with arbitrary small error by a linear combination $\sum c_n g(t - \lambda_n)$ with an l_q estimate of the coefficients:

$$\|\{c_n\}\|_{l_q} \leq C(q)\|f\|.$$

This can not be done for $q = 2$, according to [2].

Keywords: translates · frames · completeness with estimate of coefficients

Mathematics Subject Classification: 42C15 · 42C30

1. INTRODUCTION. RESULTS.

1.1. Let Λ be a uniformly discrete set of real numbers:

$$\inf_{\lambda \neq \lambda'} |\lambda - \lambda'| = \delta > 0, \quad \lambda, \lambda' \in \Lambda. \quad (1)$$

Given a function $g \in L^2(\mathbb{R})$, consider the family of translates

$$\{g(t - \lambda)\}_{\lambda \in \Lambda}. \quad (2)$$

It is well known that for $\Lambda = \mathbb{Z}$ this family cannot be complete in $L^2(\mathbb{R})$. It was conjectured that the same is true for every uniformly discrete set Λ (see, for example, [12], p.149, where even a stronger conjecture related to Gabor-type systems is discussed). However, this is not the case. The following theorem was proved in [9]:

Theorem A. *Let $\Lambda = \{\lambda_n\}_{n \in \mathbb{Z}}$ be an "almost integer" spectrum:*

$$\lambda_n = n + \alpha_n : \quad 0 < |\alpha_n| \rightarrow 0 \quad (|n| \rightarrow \infty). \quad (3)$$

Supported in part by the Israel Science Foundation.

Then there exists a "generator" g such that the family (2) is complete in $L^2(\mathbb{R})$.

One may wish to construct a uniformly discrete set of translates (2) with a stronger property than just completeness. However, one should keep in mind that no family (2) can be a frame, see [2].

1.2. In [3] we introduced an intermediate property between completeness and frame, which is reproduced here in a slightly different form:

Definition 1. We say that a system of vectors $\{u_n\}$ in a Hilbert space H is a (QF) -system if the following two conditions are fulfilled:

(i) for every $q > 2$ there is a constant $C(q)$, such that given $f \in H$ and $\epsilon > 0$, one can find a linear combination

$$Q = \sum c_n u_n, \quad (4)$$

satisfying the conditions:

$$\|f - Q\| < \epsilon, \quad (5)$$

and

$$\|\{c_n\}\|_{l_q} \leq C(q)\|f\|. \quad (6)$$

(ii) (Bessel inequality) :

$$\left(\sum |\langle f, u_n \rangle|^2\right)^{\frac{1}{2}} \leq C' \|f\|, \quad \forall f \in H,$$

where the constant C' does not depend on f .

Approximation property (i) above means "completeness with l_q estimate of coefficients". Using the standard duality argument (see [3]), it can be reformulated as follows:

$$\|f\| \leq C(p) \left(\sum |\langle f, u_n \rangle|^p\right)^{\frac{1}{p}}, \quad 1/p + 1/q = 1. \quad (7)$$

If the condition (i) in Definition 1 is required for $q=2$ then it is identical to usual definition of frames. So, one may regard (QF) -systems as a sort of "quasi-frames".

One may ask about the relation of (QF) -systems to p -frames defined in [1]. Notice that in the case of Hilbert space, p -frames may only exist for $p = 2$, when they are identical to usual frames.

1.3. In [3] we have constructed sparse exponential systems

$$E(\Lambda) := \{e^{i\lambda x}\}_{\lambda \in \Lambda}$$

which are (QF) -systems in $L^2(S)$ for "generic" sets S of large measure. Observe that these systems cannot be frames, due to celebrated Landau's density theorem.

The goal of this work is to present a similar construction for the translates. Our main result is the following

Theorem 1. *There exist a uniformly discrete sequence $\Lambda = \{\lambda_n\}$ and a function $g \in L^2(\mathbb{R})$, such that the system (2) is a (QF) -system for $L^2(\mathbb{R})$.*

We will prove this result in a stronger form, showing that Λ can be chosen sparse:

Theorem 2. *Given a sequence of positive numbers $\{\epsilon_n\} = o(1)$, one can choose Λ in Theorem 1 so that*

$$\frac{\lambda_{n+1}}{\lambda_n} > 1 + \epsilon_n. \quad (8)$$

Clearly, if ϵ_n decreases slowly enough then the gaps in the spectrum Λ grow "almost exponentially". This condition is sharp, see Remark 2.3 below. Observe that in the context of completeness, this lacunarity condition probably first appeared in [10], see also [6] and [3].

Some remarks on Theorems 1 and 2 are presented in section 2. In particular, we show (Propositions 1 and 2) that the generator g in these theorems can be chosen infinitely smooth but it cannot decrease fast at infinity.

2. PROOFS.

2.1. Following [9] we start with a reformulation of the result.

For $f \in L^2(\mathbb{R})$, we denote by $\hat{f}$ its Fourier transform:

$$\hat{f}(t) = \frac{1}{\sqrt{2\pi}} \int_{\mathbb{R}} f(x) e^{ixt} dx.$$

Definition 2. *A function $w(x) \in L^1(\mathbb{R})$ is called a weight if it is strictly positive almost everywhere on $\mathbb{R}$ (with respect to the Lebesgue measure).*

Let us consider the weighted space

$$L_w^2(\mathbb{R}) = \{f : \int_{\mathbb{R}} |f(x)|^2 w(x) dx < \infty\},$$

with the scalar product $\langle f, g \rangle = \int f(x) \bar{g}(x) w(x) dx$.

Due to the Parseval equality for the Fourier transform, the transformation

$$U_w : f \mapsto \widehat{fw^{\frac{1}{2}}}$$

is a unitary operator acting from $L_w^2(\mathbb{R})$ onto $L^2(\mathbb{R})$.

We set

$$g(t) := \widehat{\sqrt{w}}.$$

Obviously, $g \in L^2(\mathbb{R})$, and we have:

$$U_w(e^{i\lambda x}) = g(t - \lambda).$$

Since the (QF) -property of a system of vectors is invariant with respect to unitary operators, we conclude that the system $\{g(t - \lambda)\}_{\lambda \in \Lambda}$ satisfies this property in $L^2(\mathbb{R})$, if the system $E(\Lambda) := \{e^{i\lambda x}\}_{\lambda \in \Lambda}$ does so in the space $L_w^2(\mathbb{R})$. Therefore, Theorem 2 is a consequence of the following

Theorem 3. *There exist a weight $w(x)$ and a uniformly discrete set Λ such that*

- (i) Λ satisfies (8) for a pre-given sequence $\{\epsilon_n\}$;
- (ii) The system $E(\Lambda)$ is a (QF) -system in $L_w^2(\mathbb{R})$.

Remark 2.1. Reversing the argument above, one can deduce Theorem 3 from Theorem 2, so that these results are equivalent.

Our goal now is to prove Theorem 3.

2.2. We need some lemmas.

Lemma 1. *Let Λ be a uniformly discrete sequence and v be a weight such that $h := \widehat{\sqrt{v}}$ is supported by $[-\frac{\delta}{2}, \frac{\delta}{2}]$ where δ is the separation constant defined in (1). Then $E(\Lambda)$ is a Bessel system in $L_v^2(\mathbb{R})$.*

Proof. The set of translates $\{h(t - \lambda)\}$ is an orthogonal system of vectors in $L^2(\mathbb{R})$ with bounded norms, so it is a Bessel system in the space. The argument above shows that this system is obtained from $E(\Lambda)$ by the action of the unitary operator

$$U_v : L_v^2(\mathbb{R}) \rightarrow L^2(\mathbb{R}).$$

The lemma follows. □

Remark 2.2. An equivalent definition of a Bessel system in H :

$$\left\| \sum a_n u_n \right\|_H \leq C' \| \{a_n\} \|_{l_2}$$

(see [13], p.155), clearly extends the result above to every weight w , such that $w(x) \leq v(x)$ almost everywhere.

Given a trigonometric polynomial $Q(x) = \sum_{\lambda \in \Lambda} c_\lambda e^{i\lambda x}$, we set

$$\text{spec } Q = \{\lambda \in \Lambda : c_\lambda \neq 0\},$$

and

$$\|Q\|_q = \|\{c_\lambda\}\|_{l_q}.$$

The following lemma is well known, it goes back to Menshov-type representation theorems.

Lemma 2. *Given a segment $I \subset \mathbb{R}$ and a number $\mu > 0$, one can find a trigonometric polynomial $A(x) = \sum_{k=1}^K a_k e^{ikx}$ such that*

$$(i) \quad \|A\|_{(2+\mu)} < \mu; \quad (9)$$

$$(ii) \quad m\{x \in I : |A(x) - 1| > \mu\} < \mu. \quad (10)$$

For proof see [5], Chapter 4 section 2.5, or [6], Lemma 4.1 and remark 2 on p.382.

Lemma 3. *Given a segment $I \subset \mathbb{R}$, a number $\xi > 0$ and a function $f \in L^2(I)$, one can find a trigonometric polynomial $B(x) = \sum_{n=1}^N b_n e^{i\beta_n x}$ such that*

$$(i) \quad 0 \leq \beta_n - n < \xi \quad n = 1, 2, 3 \dots N; \quad (11)$$

$$(ii) \quad m\{x \in I : |f(x) - B(x)| > \xi\} < \xi. \quad (12)$$

This can be easily deduced from Landau's theorem [8], or from [9].

Lemma 4. *Let $I \subset \mathbb{R}$ be a segment. For every $\delta > 0$ and $f \in L^2(I)$, there exists a number $l > 0$ such that, given an integer $d > 0$, one can find a trigonometric polynomial $Q(x) = \sum_{m=1}^M c_m e^{i\lambda_m x}$ which satisfies*

$$(i) \quad \|Q\|_{(2+\delta)} < \delta; \quad (13)$$

$$(ii) \quad \lambda_1 \geq d; \quad (14)$$

$$(iii) \quad \frac{\lambda_{m+1}}{\lambda_m} > 1 + l, \quad m = 1, 2, 3 \dots M; \quad (15)$$

$$(iv) \quad m\{x \in I : |f(x) - Q(x)| > \delta\} < \delta. \quad (16)$$

Proof. We can assume that $I = [-\pi s, \pi s]$ for some integer $s > 0$.

Given $f \in L^2(I)$ and $0 < \delta < 1$, denote $\xi = \frac{\delta}{2}$ and use Lemma 3 to find a trigonometric polynomial,

$$B(x) = \sum_{n=1}^N b_n e^{i\beta_n x},$$

for which (11) and (12) hold.

Denote

$$\mu = \frac{\delta}{2N \max\{1, \|B\|_{(2+\delta)}\}}, \quad (17)$$

and use Lemma 2 to find a trigonometric polynomial,

$$A(x) = \sum_{k=1}^K a_k e^{ikx},$$

for which (9) and (10) hold. Set

$$l = \frac{1}{2+K}. \quad (18)$$

Given a positive integer $d > 0$, denote

$$r_n = d(K+1)^{n-1} \quad (19)$$

and define

$$Q(x) = \sum_{m=1}^M c_m e^{i\lambda_m x} := \sum_{n=1}^N b_n e^{i\beta_n x} A(r_n x),$$

where $\lambda_1 < \lambda_2 < \lambda_3 < \dots$

Denote

$$J_n := \text{spec}(e^{i\beta_n x} A(r_n x))$$

and use (11) to check that J_{n+1} follows J_n , for every $1 \leq n < N$. In particular, this fact combined with (9) and (17) means that

$$\|Q\|_{(2+\delta)} = \|A\|_{(2+\delta)} \|B\|_{(2+\delta)} \leq \|A\|_{(2+\mu)} \|B\|_{(2+\delta)} < \mu \|B\|_{(2+\delta)} < \delta.$$

So property (i) holds for Q .

From (19) we have $\lambda_1 = \beta_1 + r_1 = \beta_1 + d$, so property (ii) follows from (11).

To establish property (iii) note that there are two possible locations for λ_m and λ_{m+1} in the spectrum of Q . First, they can both belong to J_n , for some $1 \leq n \leq N$. In this case

$$\frac{\lambda_{m+1}}{\lambda_m} = \frac{\beta_n + (k+1)r_n}{\beta_n + kr_n} \quad \text{for some } 1 \leq k < K.$$

On the other hand, λ_m can be the last frequency in J_n , for some $1 \leq n \leq N$, while λ_{m+1} is the first frequency in J_{n+1} . In this case

$$\frac{\lambda_{m+1}}{\lambda_m} = \frac{\beta_{n+1} + r_{n+1}}{\beta_n + Kr_n}.$$

In both cases it is easy to see that (11), (18) and (19) imply that (iii) holds for Q .

To finish the proof we need to show that property (iv) holds for Q . Note that $I = [-\pi s, \pi s]$, so from (10), (12) and (17), we have

$$\begin{aligned} m\{x \in I : |f(x) - Q(x)| > \delta\} &\leq \\ m\{x \in I : |f(x) - B(x)| > \frac{\delta}{2}\} + m\{x \in I : |B(x) - Q(x)| > \frac{\delta}{2}\} &< \\ \frac{\delta}{2} + m\{x \in I : |\sum_{n=1}^N b_n e^{i\beta_n x} (1 - A(r_n x))| > \frac{\delta}{2}\} &\leq \end{aligned}$$

$$\begin{aligned} \frac{\delta}{2} + \sum_{n=1}^N m\{x \in I : |b_n(1 - A(r_n x))| > \frac{\delta}{2N}\} \leq \\ \frac{\delta}{2} + Nm\{x \in I : |1 - A(x)| > \frac{\delta}{2N\|\{b_n\}\|_{l_{(2+\delta)}}}\} < \delta \end{aligned}$$

which completes the proof. $\square$

We are now ready to prove Theorem 3.

Let $0 < \epsilon_n \rightarrow 0$, we can assume that $\epsilon_{n+1} < \epsilon_n$ for every n . Fix an arbitrary weight $v(x)$ with $\widehat{(\sqrt{v})}$ supported on $[-1, 1]$ and $\int v dx = 1$. Choose a sequence of functions $f_k \in C(\mathbb{R})$, $f_k(x) = 0$ for every $|x| > k$, which is dense in $L_v^2(\mathbb{R})$ (as it will automatically be in every space $L_w^2(\mathbb{R})$, $w \leq v$).

We construct the sequence Λ by induction. At the k -th step assume that $\{\lambda_n\}_{1 \leq n < N}$ have already been defined (where $N = N(k-1)$). For the segment $[-k, k]$, the function f_k and $\delta = \frac{1}{2^k}$, we use Lemma 4 to find a number $l_k > 0$. Let $n_k \geq N$ be the first number for which

$$\epsilon_{n_k} < l_k. \quad (20)$$

Choose arbitrary $\lambda_N, \lambda_{N+1}, \lambda_{N+2}, \dots, \lambda_{(n_k-1)}$ so that (8) holds for every $n < n_k$ and a number d_k for which

$$\frac{d_k}{\lambda_{(n_k-1)}} > 1 + \epsilon_{(n_k-1)}. \quad (21)$$

Use Lemma 4 to find a trigonometric polynomial Q_k so that properties (13) – (16) hold for f_k, δ_k, l_k, d_k and Q_k . Add all of $\text{spec } Q_k$ as a block from the point n_k forward to form the sequence $\{\lambda_n\}_{1 \leq n < N(k)}$.

Set $\Lambda = \{\lambda_n\}_{n=1}^\infty$ and note that the combination of properties (14), (15), (20), and (21) ensures that (8) holds for Λ .

To define the weight w denote

$$E_k = \{x \in [-k, k] : |f_k(x) - Q_k(x)| < \delta_k\}. \quad (22)$$

From (16) we have

$$m\{[-k, k] \setminus E_k\} < \delta_k. \quad (23)$$

Define

$$w(x) := v(x) \inf_k \{\mathbb{1}_{E_k}(x) + \eta_k \mathbb{1}_{\mathbb{R}/E_k}(x)\},$$

where $\mathbb{1}_E$ is the indicator function of E and $\eta_k = (2k\|f_k - Q_k\|_{L_v^2(\mathbb{R})})^{-2}$. Since $\sum_k \delta_k < \infty$, (23) implies that $0 < w \leq v$ almost everywhere.

Moreover, from (22) we have

$$\int |f_k - Q_k|^2 w dx < (\delta_k)^2 \int_{E_k} v dx + \eta_k \int_{\mathbb{R}/E_k} |f_k - Q_k|^2 v dx,$$

so

$$\|f_k - Q_k\|_{L_w^2(\mathbb{R})} < \frac{1}{k}. \quad (24)$$

Clearly Λ is a uniformly discrete sequence. Moreover, we may suppose $\{\epsilon_n\}$ to decrease so slowly that the constant in (1) satisfies $\delta > 1$, so we can use Remark 2.2 to deduce that $E(\Lambda)$ is a Bessel system in $L_w^2(\mathbb{R})$.

Fix $q > 2$. The proof will be complete if we show that, for any $f \in L_w^2(\mathbb{R})$ with $\|f\| = 1$ and $\mu > 0$, there exists a trigonometric polynomial Q such that $\text{spec} Q \subset \Lambda$, $\|f - Q\|_{L_w^2(\mathbb{R})} < \mu$ and $\|Q\|_q \leq 1$.

Given such f and $\mu > 0$, choose k large enough so that

$$2 + \delta_k < q \quad (25)$$

$$\|f - f_k\|_{L_w^2(\mathbb{R})} < \frac{\mu}{2} \quad (26)$$

$$k\mu > 2. \quad (27)$$

We claim that for the polynomial $Q = Q_k$ all of the properties described above hold. Indeed, from (13) and (25) we have

$$\|Q\|_q \leq \|Q\|_{(2+\delta_k)} \leq \delta_k \leq 1,$$

while (24) (26) and (27) imply that $\|f - Q_k\| < \mu$. This ends the proof. $\square$

2.3. Here we discuss the "time-frequency" localization of the generator g .

Proposition 1. *As in [9], one can construct the function g in Theorems 1 and 2 to be infinitely smooth and even the restriction to $\mathbb{R}$ of an entire function.*

Proof. Indeed, in the proof of Theorem 3 it is enough to start with a weight $v_0 \leq v$ with sufficiently fast decay, so the same will be true for w . The relation

$$g(t) := \widehat{(\sqrt{\cdot}(w))}.$$

implies the required property. $\square$

On the other hand, the weight w , constructed in Theorem 3 is "irregular", which means that the generator g decreases slowly. This is inevitable, due to the following

Proposition 2. *A generator g in Theorem 1 cannot belong to $L^1(\mathbb{R})$.*

Proof. Indeed, suppose it does. Then the corresponding weight $w(x) = |\hat{g}(x)|^2$ is continuous. The system $E(\Lambda)$ is a (QF) -system in $L_w^2(\mathbb{R})$. Clearly the same property holds in the space $L_w^2(I)$ for an interval I . The set

$$\{x \in I : w(x) > 0\}$$

is an open set of full measure. Take a finite union of intervals $S \subseteq I$ such that:

$$mS > \frac{mI}{2} \quad ; \quad \inf_{x \in S} w(x) > 0.$$

Clearly $E(\Lambda)$ is a (QF) -system in $L^2(S)$. Now we use Theorem 1 from [3], where it is proved that if S is a finite union of intervals and the system $E(\Lambda)$ satisfies the condition (i) in the Definition 1 (with some $q > 2$), then the Beurling-Landau estimate:

$$D^-(\Lambda) \geq \frac{mS}{2\pi}$$

still holds. This contradicts (1), if mI is sufficiently large. □

As a contrast, notice that in Theorem A, for an appropriate uniformly discrete Λ , the generator g may belong to the Schwartz space $S(R)$, see [11].

We conclude by a couple of other remarks.

Remark 2.3. The lacunarity condition in Theorems 2 and 3 is sharp. Indeed, it is well known (see [4]) that if Λ is lacunary in the Hadamard sense, that is $\lambda_{n+1}/\lambda_n > c > 1$, then the system $\{e^{i\lambda t}\}_{\lambda \in \Lambda}$ cannot be complete in $L_w^2(\mathbb{R})$.

Remark 2.4. By appropriate modification of the proof of Theorem 3, Λ in this result (as well as in Theorems 1 and 2) can be made a "small perturbation" of integers, as in the equality (3). However, again, in contrast to Theorem A, the perturbations are not arbitrary. In particular α_n cannot decrease as $O(|n|^{-s})$, $s > 0$. This can be proved similarly to the corresponding remark in [7].

REFERENCES

- [1] A. Aldroubi, Q. Sun, and W. S. Tang, p -frames and shift invariant subspaces of L^p , J. Fourier Anal. Appl. 7, no. 1 (2001), 1-21.
- [2] O. Christensen, B. Deng and C. Heil, Density of Gabor frames, Appl. Comp. Harm. Anal. 7 (1999), 292-304.
- [3] S.N. Hahamov and A. Olevskii, Sparse exponential systems: completeness with estimates, Israel Jour. of Math 158 (2007), 205-215.
- [4] P. Hartman, The divergence of non-harmonic gap series, Duke Math. J. (1942) 404-305.

- [5] Y. Katznelson, An introduction to Harmonic Analysis, 2nd ed., Dover Publications, Inc., New York, 1976.
- [6] G. Kozma, A. Olevskii, Menshov representation spectra, J. Analyse Math. 84 (2001) 361-393.
- [7] G. Kozma, A. Olevskii, Random Menshov spectra, Proc. Amer. Math. Soci. 131, no 6 (2003), 1901-1906.
- [8] H.J. Landau, A sparse sequence of exponentials closed on large sets, Bull. Am. Math. Soc.(1964)., 70, 566569.
- [9] A. Olevskii, Completness in $L^2(\mathbb{R})$ of almost integer translates, C. R. Acad. Sci. Paris, Ser. I 324 (1997), 987-991.
- [10] A. Olevskii, Approximation by translates in $L^2(\mathbb{R})$, Real Anal. Exch. 24, no 1 (1998/9), 43-44.
- [11] A. Olevskii, A. Ulanovskii, Almost integer translates, Do nice generators exist?, J. of Fourier Anal. Appl. 10, no.1 (2004), 93-104.
- [12] J. Ramanathan, T. Steger, Incompleteness of sparse coherent states, App. and Comp. Harmonic Anal., 2,(1995), 148-153.
- [13] R. Young, An introduction to nonharmonic Fourier series, Academic Press, New York, (1980).